

# Pipe Plug Immersion Heaters

## 1-1/4" NPT Pipe Plug - 1 Element

### Copper Element with Foldback Brass Pipe Plug

				FIG. 9		FIG. 10		FIG. 11		FIG. 12	
WATTS	VOLTS	WATT/ SQ. IN.	B IMM. LENGTH	A TOTAL LENGTH	CATALOG NUMBER	C TOTAL LENGTH	CATALOG NUMBER	D TOTAL LENGTH	CATALOG NUMBER	E TOTAL LENGTH	CATALOG NUMBER
1000	120	46	6 <sup>1</sup> / <sub>8</sub>	10 <sup>5</sup> / <sub>16</sub>	KIX-1-0001-M1	9 <sup>7</sup> / <sub>16</sub>	KIX-1-0001-M7	11 <sup>1</sup> / <sub>16</sub>	KIX-1T1-0001-M1	13 <sup>3</sup> / <sub>8</sub>	KIX-1T1-0001-M7
1000	240	46			KIX-1-0002-M1		KIX-1-0002-M7		KIX-1T1-0002-M1		KIX-1T1-0002-M7
1500	120	45	9 <sup>1</sup> / <sub>16</sub>	13 <sup>1</sup> / <sub>2</sub>	KIX-1-0003-M1	13 <sup>1</sup> / <sub>16</sub>	KIX-1-0003-M7	14 <sup>3</sup> / <sub>8</sub>	KIX-1T1-0003-M1	16 <sup>5</sup> / <sub>16</sub>	KIX-1T1-0003-M7
1500	240	45			KIX-1-0004-M1		KIX-1-0004-M7		KIX-1T1-0004-M1		KIX-1T1-0004-M7
2000	120	90	6 <sup>3</sup> / <sub>8</sub>	11 <sup>1</sup> / <sub>16</sub>	KIX-1-0005-M1	10 <sup>3</sup> / <sub>8</sub>	KIX-1-0005-M7	12 <sup>3</sup> / <sub>16</sub>	KIX-1T1-0005-M1	13 <sup>3</sup> / <sub>8</sub>	KIX-1T1-0005-M7
2000	240	90			KIX-1-0006-M1		KIX-1-0006-M7		KIX-1T1-0006-M1		KIX-1T1-0006-M7
2500	240	79	8 <sup>1</sup> / <sub>2</sub>	12 <sup>1</sup> / <sub>16</sub>	KIX-1-0007-M1	12 <sup>1</sup> / <sub>2</sub>	KIX-1-0007-M7	14 <sup>1</sup> / <sub>16</sub>	KIX-1T1-0007-M1	15 <sup>3</sup> / <sub>4</sub>	KIX-1T1-0007-M7
3000	240	79	10 <sup>3</sup> / <sub>16</sub>	14 <sup>1</sup> / <sub>4</sub>	KIX-1-0008-M1	14 <sup>3</sup> / <sub>16</sub>	KIX-1-0008-M7	15 <sup>3</sup> / <sub>8</sub>	KIX-1T1-0008-M1	17 <sup>1</sup> / <sub>16</sub>	KIX-1T1-0008-M7
4000	240	79	13 <sup>3</sup> / <sub>16</sub>	18	KIX-1-0009-M1	17 <sup>7</sup> / <sub>16</sub>	KIX-1-0009-M7	19 <sup>1</sup> / <sub>8</sub>	KIX-1T1-0009-M1	20 <sup>1</sup> / <sub>16</sub>	KIX-1T1-0009-M7
5000	240	78	16 <sup>1</sup> / <sub>16</sub>	21 <sup>1</sup> / <sub>8</sub>	KIX-1-0010-M1	20 <sup>1</sup> / <sub>16</sub>	KIX-1-0010-M7	22 <sup>1</sup> / <sub>2</sub>	KIX-1T1-0010-M1	24 <sup>3</sup> / <sub>16</sub>	KIX-1T1-0010-M7

### Stainless Steel Element with Foldback Stainless Steel Pipe Plug

WATTS	VOLTS	WATT/ SQ. IN.	B IMM. LENGTH	A TOTAL LENGTH	CATALOG NUMBER	C TOTAL LENGTH	CATALOG NUMBER	D TOTAL LENGTH	CATALOG NUMBER	E TOTAL LENGTH	CATALOG NUMBER
1000	120	46	6 <sup>3</sup> / <sub>8</sub>	10 <sup>5</sup> / <sub>16</sub>	KJX-1-0001-M1	9 <sup>7</sup> / <sub>16</sub>	KJX-1-0001-M7	11 <sup>1</sup> / <sub>16</sub>	KJX-1T1-0001-M1	13 <sup>3</sup> / <sub>8</sub>	KJX-1T1-0001-M7
1000	240	46			KJX-1-0002-M1		KJX-1-0002-M7		KJX-1T1-0002-M1		KJX-1T1-0002-M7
1500	120	45	9 <sup>1</sup> / <sub>16</sub>	13 <sup>1</sup> / <sub>2</sub>	KJX-1-0003-M1	13 <sup>1</sup> / <sub>16</sub>	KJX-1-0003-M7	14 <sup>3</sup> / <sub>8</sub>	KJX-1T1-0003-M1	16 <sup>5</sup> / <sub>16</sub>	KJX-1T1-0003-M7
1500	240	45			KJX-1-0004-M1		KJX-1-0004-M7		KJX-1T1-0004-M1		KJX-1T1-0004-M7
2000	120	90	6 <sup>3</sup> / <sub>8</sub>	11 <sup>1</sup> / <sub>16</sub>	KJX-1-0005-M1	10 <sup>3</sup> / <sub>8</sub>	KJX-1-0005-M7	12 <sup>3</sup> / <sub>16</sub>	KJX-1T1-0005-M1	13 <sup>3</sup> / <sub>8</sub>	KJX-1T1-0005-M7
2000	240	90			KJX-1-0006-M1		KJX-1-0006-M7		KJX-1T1-0006-M1		KJX-1T1-0006-M7
2500	240	79	8 <sup>1</sup> / <sub>2</sub>	12 <sup>1</sup> / <sub>16</sub>	KJX-1-0007-M1	12 <sup>1</sup> / <sub>2</sub>	KJX-1-0007-M7	14 <sup>1</sup> / <sub>16</sub>	KJX-1T1-0007-M1	15 <sup>3</sup> / <sub>4</sub>	KJX-1T1-0007-M7
3000	240	79	10 <sup>3</sup> / <sub>16</sub>	14 <sup>1</sup> / <sub>4</sub>	KJX-1-0008-M1	14 <sup>3</sup> / <sub>16</sub>	KJX-1-0008-M7	15 <sup>3</sup> / <sub>8</sub>	KJX-1T1-0008-M1	17 <sup>1</sup> / <sub>16</sub>	KJX-1T1-0008-M7
4000	240	79	13 <sup>3</sup> / <sub>16</sub>	18	KJX-1-0009-M1	17 <sup>7</sup> / <sub>16</sub>	KJX-1-0009-M7	19 <sup>1</sup> / <sub>8</sub>	KJX-1T1-0009-M1	20 <sup>1</sup> / <sub>16</sub>	KJX-1T1-0009-M7
5000	240	78	16 <sup>1</sup> / <sub>16</sub>	21 <sup>1</sup> / <sub>8</sub>	KJX-1-0010-M1	20 <sup>1</sup> / <sub>16</sub>	KJX-1-0010-M7	22 <sup>1</sup> / <sub>2</sub>	KJX-1T1-0010-M1	24 <sup>3</sup> / <sub>16</sub>	KJX-1T1-0010-M7